



CONNECT

QCM

Quick Connect with Manual Transfer Switch

Lake Shore Electric's QCM (Quick Connect with Manual Transfer Switch) seamlessly integrates the safety and reliability of a Manual Transfer Switch with the ease and efficiency of a Quick Connection Cabinet - ensuring full compliance with NEC 700.3(F).

All QCM's feature an application-specific internal mechanical interlock designed to prevent the paralleling of both sources. This interlock does not require a key, ensuring simple and straightforward operation.



Model: 800A - 1200A

Standard Features

- Two Mechanically Interlocked UL 489 Switches
- Color-Coded Camlock Receptacles
- Source Available & Switch Position Auxiliary Contacts & Indicating Lights
- 2-Wire Start Binding Post
- NEMA 5-20R GFCI Receptacle
- NEMA 3R Enclosure

Options & Accessories

- Service Entrance Rated
- Phase Rotation Monitor
- Space Heater
- Alternate Source Over Current Protection
- 304 or 316 Stainless Steel Enclosure
- Leg Kit (150A - 400A)



Model: 150A - 400A

QCM ENCLOSURE SPECIFICATIONS

Amperage	Enclosure Type	H x W x D
150	Wall Mount ¹	47" x 40" x 22"
400		
800		
1200	Pad Mount	90" x 72" x 36"
1600	Pad Mount	90" x 108" x 36"
2000		
3200		
4000		

¹ Enclosure available in wall mount only. Leg Kit sold separately.

lseconnect.com/qcm